

LEGACY BULB REPLACEMENT CHART **LANDING**

INCANDESCENT						AEROLEDS CERTIFIED				
Size	Model	Voltage	Watts	Peak	Lumens	Model				
PAR36	H7604	14	50	50,000	750	SunSpot 36 LXi 01-1030-L-A Volts: 9-30 Watts: 45 Candela: 140,000 Lumens: 5,000	SunSpot 36-4509 01-1030-4509 01-1030-4509-H Volts: 14 Watts: 75 Candela: 200,000 Lumens: 8,250	SunSpot 36-4313 01-1030-4313 01-1030-4313-H Volts: 14 Watts: 95 Candela: 200,000 Lumens: 11,000	SunSpot 36-Equinox Dual-Function LED Landing/Taxi Light 01-1030-LT-12 Volts: 14 Watts: 100/75 Candela: 215,000 /65,000 Lumens: 11,000	
	4509		100	60,000	1,500					
	4595									
	4700									
	Q4632		250	75,000	3,750					
	Q4631									
	4313	90,000								
	4591	28	100	20,000	1,500		SunSpot 36-4591 01-1030-4591 01-1030-4591-H Volts: 28 Watts: 75 Candela: 200,000 Lumens: 8,250	SunSpot 36-4596 01-1030-4596 01-1030-4596-H Volts: 28 Watts: 100 Candela: 215,000 Lumens: 11,000		SunSpot 36-Equinox Dual-Function LED Landing/Taxi Light 01-1030-LT-24 Volts: 28 Watts: 100/100 Candela: 210,000 /65,000 Lumens: 11,000
	Q4591									
	Q5587		250	40,000	3,750					
4596										
Q5596	150,000									
PAR46	4522	14	250	290,000	3,750	SunSpot 46 LX/HX 01-2130-LX 01-2130-HX Volts: 9-40 Watts: 85 Candela: 150,000 Lumens: 9,250	SunSpot 46-4522 01-2230-4522 Volts: 14 Watts: 140 Candela: 180,000 Lumens: 15,400	SunSpot 46-Equinox Dual-Function LED Landing/Taxi Light 01-2230-LT-12 Volts: 14 Watts: 145/135 Candela: 230,000/50,000 Lumens: 15,000		
	4553								28	450
	Q4566	300,000								
	Q4681	150,000								
	4580	400,000								
	4581									
PAR64	4552	28	250	500,000	4,000	SunSpot 64-4559 01-2250-4559 Volts: 28 Watts: 200 Candela: 420,000 Lumens: 22,000				
	Q4559								600	765,000
	4559									
	Q4559X									
	Q4559XX									
	Q5559									