

## **Installation Instructions**

**Pulsar N-Series (Experimental)** 



AeroLEDs, LLC 8475 W. Elisa St. Boise, ID, 83709 208-850-3294

**NOTE:** A <u>printed copy</u> of this document may not be the latest revision. It is the responsibility of the user to ensure that the latest revision is used. The latest revision of this document may be printed from the AeroLEDs electronic document repository. Revision history follows on page 2

This document contains proprietary information of AeroLEDs. Neither receipt nor possession thereof confer any right to reproduce or use, or disclose, in whole or in part, any such information without written permission from AeroLEDs.

Approval	Name	Intent			
Author	Jennifer Blanchfield	Installation instructions for Every			
Check	Nate Calvin	Installation instructions for Experimental Pulsar N-series light assemblies (01-1280-			
Quality	Mark McCormack	B/C)	(1		
Date:	July 13, 2023	1			
<b>Status:</b> Released	Typed signatures indicate approval. Handwritten, or electronic signature approval of this document is on file at AeroLEDs, Boise, Idaho.	Document Number 0008-0022	Revision F		

## **REVISION RECORD**

Rev	Description	Date	Author
F	Updated – mounting diagram image	7/13/2023	J. Blanchfield
Е	Updated - information, tables, and wiring diagrams	08/26/2022	J. Blanchfield
D	Add new Logo, added * note on Table 1	05/03/2022	J. Blanchfield
С	Revising Model Numbers Table	07/06/2020	J. Blanchfield
В	Format, Instruction, and Image updates	4/20/2020	J. Blanchfield
Α	Updated	12/17/2019	R. Prew
IR	Original Version	12/06/2016	D. Wilkinson

# **TABLE OF CONTENTS**

1	S	System Description				
		Model Numbers				
	Airworthiness Limitations					
		Instructions for Continued Airworthiness				
4	In	stallation	. 5			
	4.1	Installation Procedures	. 5			
	4.2	Troubleshooting	. 6			
5	D	agrams	. 6			
	5.1	Mounting diagram	. 6			
	5.2	Bracket diagram	. 7			
	5.3	Wiring diagram	. 7			

## 1 System Description

The Pulsar N-Series LED lights offer the capability to have three functions in one unit: Navigation, Anti-Collision Strobe, and Position. These lights are designed for installation on any aircraft wingtip, aft stabilizer, or fuselage.

TSO-C30c TYPE I, II & III – APPROVED

TSO-C96a CLASS II - APPROVED

## 2 **Model Numbers**

			Voltage	Current (Amps)		Weight	
Model	Part Number	Description	(VDC)	Stro	Strobe		(0-)
				AVG	Peak	INAV	, ,
Pulsar NS-(12V)	01-1280-B-12-L	Novigation Anti-collision					
01-1280-B-12	01-1280-B-12-R	Navigation, Anti-collision	1.3	9.8	1.6		
Pulsar NSP-(12V)	01-1280-C-12-L	Navigation, Position, Anti-collision	9-15	9-15 1.3	9.0	1.0	
01-1280-C-12	01-1280-C-12-R	navigation, Position, Anti-comsion				7.6*	
Pulsar NS-(24V)	01-1280-B-24-L	- Navigation, Anti-collision	18-30 0.8		6.1	0.8	7.0
01-1280-B-24	01-1280-B-24-R			0.8			
Pulsar NSP-(24V)	01-1280-C-24-L	Navigation, Position, Anti-collision		0.6	0.1		
01-1280-C-24	01-1280-C-24-R						

Table 1

Note: All listed specifications shown are per pair

## 3 Airworthiness Limitations

The Airworthiness Limitations section is FAA approved and specifies maintenance required under **14 CFR**, **§43.16** and **14 CFR**, **§91.403** of the Federal Aviation Regulations unless an alternative program has been FAA approved. There are no additional airworthiness limitations.



<sup>\*</sup>Includes weight of two mounting brackets (.5 oz)

#### 3.1 Instructions for Continued Airworthiness

Pulsar light assemblies contains no user serviceable items. Should any LED fail, unit must be replaced.

Interval	Inspection	Remedy	Notes
Pre-Flight	Perform a functional check and observe that all LEDs are illuminated	If all LEDs are not illuminated replace light as soon as is practicable	<ul><li>Lights are not user serviceable.</li><li>Lights are very</li></ul>
Annually, unless the OEM specifies a shorter interval	<ul> <li>Perform a functional check and observe that all LEDs are illuminated</li> <li>Check mounting, connections, and wire integrity</li> </ul>	<ul> <li>If all LEDs are not illuminated, the light must be replaced</li> <li>Adjust or replace wiring, and connectors as required</li> </ul>	bright and to reduce eye strain during inspection use an optical filter such as dark glasses or welding goggles.

Table 2

## 4 Installation

Consult **14CFR**, **§43.13-1B** for guidance on acceptable methods, techniques, and practices. Pulsar lights mount onto a supplied bracket, which mounts into existing holes on aircraft (see mounting diagram). For retrofit installation existing circuit breaker or fuse may typically be used. Procedures contained herein are not intended to conflict with procedures set forth by aircraft OEM, nor do they supersede FAA approved manuals and FAA regulations.

#### 4.1 Installation Procedures

- 1. Disconnect aircraft power or disable applicable circuit breakers
- 2. Ensure all switches are in the OFF position
- 3. Reference OEM manual
  - a. Remove existing light assembly (retain hardware)
  - b. Bypass or remove existing high voltage power supply (if applicable)

# NOTE: Connecting light to high voltage power supply will result in permanent damage and will void warranty

- 4. Install suitable connecters and/or splices to connect light assemblies in accordance with wiring diagram(s)
- 5. Using the appropriate hardware install as per section **5.1 Mounting diagram**
- 6. Re-connect aircraft power or enable applicable circuit breakers
- 7. Verify proper operation of LED light(s)
- 8. Record installation with logbook entry

**Note:** Shielded cable is recommended although not required for installation.

It is recommended that ground connections for all lights be made at a single location on aircraft central ground bus. This "single point ground" scheme helps to eliminate ground loops and ground bounce that can occur when using airframe as a ground.





#### 4.2 Troubleshooting

- 1. Check for proper voltage at power input wire to light
- 2. Ensure light is adequately grounded
- 3. Check for continuity in wiring and connections
- 4. If wiring is verified, remove light and bench-check with appropriately sized power supply

If above actions do not correct problem, contact AeroLEDs tech support at 1-208-850-3294 for a resolution.

## 5 **Diagrams**

## 5.1 Mounting diagram




Image 1

### 5.2 Bracket diagram




Image 2

## 5.3 Wiring diagram

**WARNING:** Do not connect the strobe power wire to a Xenon strobe power pack. This will damage light and voids warranty.




Image 3